
LCBT-CB5

Casambi Bluetooth + RF CV LED Controller 5CH x 3A



PRODUCT OVERVIEW

Casambi Bluetooth + RF 5CH Constant Voltage LED Controller - DC socket or terminal screw power input, 5-channel constant voltage output, maximum output current per channel is 3A. - Multi-in-one function for controlling single color, color temperature, RGB, RGBW or RGB+CCT low voltage LED strips. - Casambi APP control, support on/off, RGB color, color temperature and brightness adjustment, group control, scene editing, minimum/maximum brightness setting, power-on startup status and multiple power-down memory function settings. - Set up multiple light types via the Casambi APP, can match with single-zone or multi-zone RF remotes with the same light types. - 10 built-in dynamic modes including jumps and fades for RGB, RGBW or RGB+CCT lighting types. - Light on/off fade time 0-3s selectable.

PRODUCT INFORMATION

CODE
LCBT-CB5

VOLTAGE INPUT
12-24VDC

VOLTAGE OUTPUT
5 x (12-24)VDC

OUTPUT POWER
5 x (36-72)W

OUTPUT CURRENT (PER CH)
5CH, 3A/CH

CHANNELS
5

DIMMING INPUT
Bluetooth + RF2.4GHz

DIMMING OUTPUT
PWM

DIMMING RANGE
0-100%

PWM FREQUENCY
2000Hz (default)

REMOTE ENABLED
Yes

STANDBY LOAD
0.5–1.0W

SAFETY
EN 61347-1/-2


PROTECTION
Reverse polarity, Overheat, short circuit

IP RATING
20

OPERATING TEMP
-20°C ~ +55°C

DIMENSIONS
L114mm x W38mm x H20mm

DIMENSIONS



While every effort has been made to ensure accuracy, product specifications may vary. Task Lighting reserves the right to update or modify product details without notice.