

LCBT-S1-CB

Casambi Bluetooth + RF Triac Dimmer

PRODUCT OVERVIEW



Casambi Bluetooth + RF Triac Dimmer - Casambi Bluetooth + RF + Push AC phase cut dimmer, 1 channel output - To dim and switch single colour dimmable LED lamps, traditional incandescent and halogen lights. - Casambi APP control, supports On/Off, brightness adjustment, group control, scene editing, Min/Max Brightness setting, power-on status and various power-down memory settings. - 256 levels of 0-100% dimming smoothly without any flash. - Minimum brightness, reverse-phase or forward-phase dimming can be set by key. - Compatibility with RF 2.4G single zone or multiple zone dimming remote control. - Connect with external push switch to achieve on/off and 0-100% dimming function. - Easy to be placed on rail or 0001in standard wall junction box. - Overheat/Overload protection, recover automatically.

PRODUCT INFORMATION

CODE	VOLTAGE INPUT
LCBT-S1-CB	AC100-240V
VOLTAGE OUTPUT	OUTPUT POWER
AC100-240V	150-360W
OUTPUT CURRENT (PER CH)	CHANNELS
Max 1.5A	1
DIMMING INPUT	DIMMING OUTPUT
BT,RF 2.4GHz,Push switch	Triac
DIMMING RANGE	REMOTE ENABLED
0-100%	Yes
STANDBY LOAD	SAFETY
0.5~1W	EN 60669-1/-2
PROTECTION	IP RATING
Overheat/Overload	20
OPERATING TEMP	DIMENSIONS
-20°C ~+55°C	L49.5mm x W56mm x H28mm

DIMENSIONS

