

LCBT-SS-CB

Casambi Bluetooth + RF Relay Switch

PRODUCT OVERVIEW

Casambi Bluetooth + RF Relay Switch

- Casambi Bluetooth +RF relay switch, 10A dry contact relay output, with zero-crossing detection function.
- For on/off single-color LED lights, conventional incandescent and halogen lamps without dimming.
- Casambi APP control, supports On/Off, group control, scene editing, power-on status and various power-down memory settings.
- Match with RF 2.4G remote control optional.
- With self-reset switch input interface.
- Built-in high surge specification relay.
- Can be mounted on a rail or in a standard wall junction box.



PRODUCT INFORMATION

CODE

LCBT-SS-CB

OUTPUT CURRENT (PER CH)

10A Resistive / 8A Driver

DIMMING INPUT

BT/RF2.4GHz /Push switch

SAFETY

EN 60669-1/-2

IP RATING

20

DIMENSIONS

L49.5mm x W56mm x H28mm

VOLTAGE INPUT

AC100-240V

CHANNELS

1

REMOTE ENABLED

Yes

PROTECTION

Overheat

OPERATING TEMP

-20°C ~+55°C

DIMENSIONS

